

**Amendments to the Claims:**

Please amend claims 1 and 9 as follows. This listing of claims will replace all prior versions and listings of claims in the application.

**Listing of Claims:**

1. (Currently Amended) An apparatus for calculating satellite acquisition information to determine a position of an mobile station (MS) in a network assisted GPS system , comprising:

a satellite data collector for collecting satellite orbital information and pseudo range between a satellite and at least one of a mobile station (MS) and a base station (BS) of more than three consecutive times from a plurality of satellites ;

a satellite velocity calculator for calculating velocity of satellites relative to the Earth-Centered, Earth-Fixed (ECEF) coordinate system using the satellite orbital information;

a pseudo velocity calculator for calculating pseudo velocities between the MS and each satellite observed by the MS at a position measurement time of the MS using the velocity of satellites; and

a satellite acquisition information calculator for calculating a code phase using the pseudo range, and for calculating a Doppler shift using the pseudo velocity.

2. (Original) The apparatus as set forth in claim 1, wherein the pseudo range is estimated considering a propagation delay between each satellite observed by the MS and the MS.

3. (Original) The apparatus as set forth in claim 1, wherein the pseudo velocity is estimated considering a propagation delay between each satellite observed by the MS and the MS.

4. (Original) The apparatus as set forth in claim 1, wherein the satellite orbital information is comprised of satellite coordinates and a coordinate extraction time.

5. (Original) The apparatus as set forth in claim 1, wherein the satellite acquisition information calculator calculates a code phase between each satellite and the MS using the following equation:

$$SV\_CODE\_PH = \text{floor}((\rho/C)*1000 - t*1023)$$
$$t = \text{floor}((\rho/C)*1000)$$

where  $SV\_CODE\_PH$  is a code phase between the satellite and the MS,  $\rho$  is a pseudo range, and  $C$  is the velocity of light.

6. (Original) The apparatus as set forth in claim 1, wherein the satellite acquisition information calculator calculates the Doppler shift containing both a frequency variation of the satellite signal at the time  $T_a$  at which the MS expects to search for the satellite signal and a differential value of the frequency variation.

7. (Original) The apparatus as set forth in claim 6, wherein the satellite acquisition information calculator calculates the frequency variation of the satellite signal received in the MS using the following equation:

$$DOPPLER0(= PV_{sv\_bts} | T_a) = PV_{sv\_gpsrv} | T_c$$
$$+ (RV_{sv\_bts} | T_a - RV_{sv\_gpsrv} | T_c) * 1000 * 1575420000 / C$$

where  $DOPPLER0$  is the frequency variation of the satellite signal,  $PV_{sv\_bts}|Ta$  is a pseudo velocity between the satellite and the MS at the time  $Ta$ ,  $PV_{sv\_gpsrv}|Tc$  is a pseudo velocity between the satellite and the apparatus at the time  $Tc$ ,  $(RV_{sv\_bts}|Ta - RV_{sv\_gpsrv}|Tc)$  is a difference between a real velocity of the satellite at the time  $Ta$  and a real velocity of the satellite at the time  $Tc$ .

8. (Original) The apparatus as set forth in claim 7, wherein the satellite acquisition information calculator calculates a differential value of the frequency variation of the satellite signal using the difference between the pseudo velocities of the times  $Ta0$  and  $Ta1$  by means of the following equation:

$$\Delta Doppler = (RV_{sv\_bts}|Ta1 - RV_{sv\_bts}|Ta0) * 1000 * 1575420000 / C$$
$$Doppler1 = \text{floor}(\Delta Doppler * 64)$$

where  $RV_{sv\_bts}|Ta0$  is a real range between the satellite and the BS at the time  $Ta$ ,  $RV_{sv\_bts}|Ta1$  is a real range between the satellite and the BS at the time  $Ta1$ ,  $C$  is a velocity of light, and  $Doppler1$  is a differential value of the frequency variation of the satellite signal.

9. (Currently Amended) A method for calculating satellite acquisition information to determine a position of an mobile station (MS) in a network assisted GPS system, the method comprising:

a) collecting satellite orbital information and pseudo range between a satellite and at least one of a mobile station (MS) and a base station (BS) of more than three consecutive times from a plurality of satellites;

b) calculating velocity of satellites relative to the Earth-Centered, Earth-Fixed (ECEF) coordinate system using the satellite orbital information ;

c) calculating pseudo velocities between the MS and the each satellite observed by the MS at a position measurement time of the MS using the velocity of

satellites; and

d) calculating a code phase using the pseudo range, and for calculating a Doppler shift using the pseudo velocity.

10. (Original) The method as set forth in claim 9, wherein the pseudo range is estimated considering a propagation delay between the each satellite observed by the MS and the MS.

11. (Original) The method as set forth in claim 9, wherein the pseudo velocity is estimated considering a propagation delay between the each satellite observed by the MS and the MS.

12. (Original) The method as set forth in claim 9, wherein the satellite orbital information is comprised of satellite coordinates and a coordinate extraction time.

13. (Original) The method as set forth in claim 9, wherein the step (d) for calculating the satellite acquisition information comprises:

d1) calculating a code phase between the each satellite and the MS using the following equation:

$$SV\_CODE\_PH = \text{floor}((\rho / C) * 1000 - t * 1023)$$
$$t = \text{floor}((\rho / C) * 1000)$$

where  $SV\_CODE\_PH$  is a code phase between the satellite and the MS,  $\rho$  is a pseudo range, and  $C$  is the velocity of light.

14. (Original) The method as set forth in claim 9, wherein the step (d) for calculating the satellite acquisition information further comprises:

d2) calculating the Doppler shift containing both a frequency variation of the satellite signal at the time  $T_a$  at which the MS expects to search for the satellite signal and a differential value of the frequency variation.

15. (Original) The method as set forth in claim 14, wherein the step (d) for calculating the satellite acquisition information further comprises:

d3) calculating the frequency variation of the satellite signal received in the MS using the following equation:

$$\begin{aligned} DOPPLER0(= PV_{sv\_bts}|Ta) &= PV_{sv\_gpsrv}|Tc \\ &+ (RV_{sv\_bts}|Ta - RV_{sv\_gpsrv}|Tc) * 1000 * 1575420000 / C \end{aligned}$$

where  $DOPPLER0$  is the frequency variation of the satellite signal,  $PV_{sv\_bts}|Ta$  is a pseudo velocity between the satellite and the MS at the time  $T_a$ ,  $PV_{sv\_gpsrv}|Tc$  is a pseudo velocity between the satellite and the apparatus at the time  $T_c$ ,  $(RV_{sv\_bts}|Ta - RV_{sv\_gpsrv}|Tc)$  is a difference between a real velocity of the satellite at the time  $T_a$  and a real velocity of the satellite at the time  $T_c$ .

16. (Original) The method as set forth in claim 15, wherein the step (d) for calculating the satellite acquisition information further comprises:

d4) calculating a differential value of the frequency variation of the satellite signal using the difference between the pseudo velocities of the times  $T_a$  and  $T_{a1}$  by means of the following equation:

$$\begin{aligned} \Delta Doppler &= (RV_{sv\_bts}|Ta1 - RV_{sv\_bts}|Ta0) * 1000 * 1575420000 / C \\ Doppler1 &= \text{floor}(\Delta Doppler * 64) \end{aligned}$$

Application No. 10/776,319  
Amendment dated July 8, 2005  
Reply to Office Action of April 8, 2005

where  $RV_{sv\_bts}|Ta0$  is a real range between the satellite and the BS at the time  $Ta$ ,  $RV_{sv\_bts}|Ta1$  is a real range between the satellite and the BS at the time  $Ta1$ ,  $C$  is the velocity of light, and  $Doppler1$  is a differential value of the frequency variation of the satellite signal.